

PACEdge

IMPORTANT PRODUCT INFORMATION



Warnings and Caution Notes as Used in this Publication

WARNING

Warning notices are used in this publication to emphasize that hazardous voltages, currents, temperatures, or other conditions that could cause personal injury exist in this equipment or may be associated with its use.

In situations where inattention could cause either personal injury or damage to equipment, a Warning notice is used.

CAUTION

Caution notices are used where equipment might be damaged if care is not taken.

Note: Notes merely call attention to information that is especially significant to understanding and operating the equipment.

These instructions do not purport to cover all details or variations in equipment, nor to provide for every possible contingency to be met during installation, operation, and maintenance. The information is supplied for informational purposes only, and Emerson makes no warranty as to the accuracy of the information included herein. Changes, modifications, and/or improvements to equipment and specifications are made periodically and these changes may or may not be reflected herein. It is understood that Emerson may make changes, modifications, or improvements to the equipment referenced herein or to the document itself at any time. This document is intended for trained personnel familiar with the Emerson products referenced herein.

Emerson may have patents or pending patent applications covering subject matter in this document. The furnishing of this document does not provide any license whatsoever to any of these patents.

Emerson provides the following document and the information included therein as-is and without warranty of any kind, expressed or implied, including but not limited to any implied statutory warranty of merchantability or fitness for particular purpose.

Introduction

PACEdge processing maximizes the value of your data by improving operational reliability, safety, and energy. PACEdge provides all aspects of edge processing and simplifies your IIoT application development, deployment, and administration. All components necessary in the IIoT application lifecycle are brought together in one package to provide a unified interface to decrease your development time and increase your deployable footprint.

This document serves as a resource for users that wish to quickly locate notes about improvements, bugs, or resolved issues as well as any auxiliary information about the PACEdge software.

Current Release Information

| Component | Version Number |
|-----------------------------|----------------|
| PACEdge | 2.2.0 |
| Movicon.NEXt Editor Support | 4.2 |
| Containers | Version Number |
| MQTT | 2.0.14 |
| MySQL (Mariadb) | 10.5.16 |
| Node-RED | 2.2.2 |
| InfluxDB | 1.8.10 |
| Chronograf | 1.9.4 |
| Grafana | 9.0.2 |
| Portainer | 2.11.1 |
| NGINX | 2.2.0 |
| Traefik | 2.8.1 |
| Telegraf | 1.23.2 |
| Connex/WebHMI | 4.2 |

Related Information

| Document Title | Document Number |
|---------------------------------|-----------------|
| PACEdge User's Manual | GFK-3178 |
| RXi2-LP Quick Start Guide | GFK-3074 |
| RXi2-BP Quick Start Guide | GFK-3196 |
| PACEdge Secure Deployment Guide | GFK-3197 |
| RXi2-BP User's Manual | GFK-3187 |
| RXi2-BP Secure Deployment Guide | GFK-3200 |

Field Upgrades

Upgrades are available for download on the Software Orders and Downloads page.

| Upgradeable Component | New Version | Part Number | Notes |
|--|------------------|-----------------------------------|---|
| PACEdge 2.1 (all HW) PACEdge 2.1.1 (all HW) | PACEdge 2.2.0 | PEv220UBUpdate PEv220AppUpdate | Two packages for upgrading from PACEdge version 2.1 or version 2.1.1 to version 2.2.0. PEv220UBUpdate is for the host Ubuntu operating system. PEv220AppUpdate is for PACEdge Applications (Free update) |
| PACEdge 2.2.0 (CPE400) | No change | IC695ACCTP0-AA | RX3i CPE400 Telemetry Protocol Option For purchase. |
| PACEdge 2.2.0 (CPL410) | No change | IC695ACCTP1-AA | RX3i CPL410 Telemetry Protocol Option For purchase. |
| PACEdge 2.2.0 (CPE400) | No change | IC695ACCFP0-AA | RX3i CPE400 Facilities Protocol Option For purchase. |

| Upgradeable Component | New Version | Part Number | Notes |
|------------------------------|------------------------|----------------------|---|
| PACEdge 2.2.0 (CPL410) | No change | IC695ACCFP1-AA | RX3i CPL410 Facilities Protocol Option For purchase. |
| PACEdge 2.2.0 (CPE400) | No change | IC695ACCMD0-AA | RX3i CPE400 Multi Drivers Option For purchase. |
| PACEdge 2.2.0 (CPL410) | No change | IC695ACCMD1-AA | RX3i CPL410 Multi Drivers Option For purchase. |
| PACEdge 2.2.2 (Rxi2-BP, -LP) | PACEdge 2.2.2 + Connex | UPGRADE_CONNEXT_LPBP | For purchase. |
| PACEdge 2.2.2 (Rxi2-BP) | PACEdge 2.2.2 + WebHMI | UPGRADE_WEBHMI_BP | For purchase. |
| UEFI | V1.10 | N/A | Contact technical support |

Important Product Information for this Release

Release History

| PACEdge SW Version | Date | Description |
|--------------------|----------|--|
| 2.2.0 | Oct 2022 | PACEdge v2.2.0 release. Main Updates: Support for Movicon v4.2 Updated Node-RED to version v2.2.2 |

| | | |
|-------|----------|---|
| | | <p>Updated Grafana to version v9.0.2</p> <p>Updated Telegraf to version v1.23.2</p> <p>Updated other applications to newer versions</p> <p>Improved PACEdge usability: (simplified password management tool, that now covers all PACEdge applications, OPC UA Port forwarding feature, PACEdge update split into OS and Application updates, PACEdge update utility that now backs up and then restores user data during an update, pre-configured databases in Grafana, Emerson Node-RED nodes and built-in examples to simplify MQTT, InfluxDB and MySQL access)</p> <p>Progea name was changed to Movicon, including use in browser paths and docker container name.</p> |
| 2.1.1 | Feb 2022 | <p>Updates, applied via Patch file:</p> <p>Updated Movicon container (Connex, WebHMI)</p> <p>Update to the license. Connex and WebHMI SKUs now enable 3 drivers and support the MQTT protocol.</p> <p>The update allows users to purchase protocol upgrades for CPL410 and CPE400 products</p> <p>Bug fix in password management utility allows the use of special characters in the password</p> |
| 2.1.0 | Dec 2021 | Release of PACEdge version 2.1 |
| 2.0.1 | Oct 2021 | Updates to Restrictions and Open Issues Section: PACEdge container logging mechanism, especially for InfluxDB, will continue to write logs into the disc, eventually filling it up. |
| 2.0.1 | Sep 2020 | Initial Release |

Functional Compatibility

| Compatibility Issue | Description |
|---|---|
| v2.2.0 update is valid only for v2.1 and v2.1.1 | Only v2.1 and v2.1.1 can be upgraded to v2.2.2. Older versions will need to be first updated to v2.1 NOTE: Please refer to the older version of the PACEdge User Manual for the upgrade procedures to PACEdge v2.1 |
| Will require a valid PACEdge 2.1 license | When upgrading from PACEdge 2.0 to PACEdge 2.1 user will have to obtain a valid license from Emerson Customer Care. |

Restrictions and Open Issues

| Subject | Description |
|---|---|
| Stop flows accessing databases before the upgrade | When upgrading to v2.2.0, stop flows that are storing data in InfluxDB and MySQL. Failure to do so might result in InfluxDB being overwhelmed by requests with the wrong password, as password change will be part of the update process. In such cases, to recover, disable Node-RED flows, give a few minutes for the InfluxDB to catch up (monitor InfluxDB container CPU utilization), update passwords in InfluxDB Node-RED nodes (if changed), and re-enable Node-RED flows. |
| Password Management utility fails | Password Management utility expects that user role passwords in each of the PACEdge applications are the same. Most importantly admin password shall be the same in all applications. If during the upgrade to v2.2.0, one of the applications has a different password, for instance, the Portainer password was never changed from default edgestack to match the Node-RED and Grafana passwords, the utility will report an error. In such a case, please manually log into the application, change the password there to match the rest of the applications, and try the Password Management utility again. |

| | |
|---|--|
| Heavy CPU and memory utilization when upgrading via Navigator | When upgrading PACEdge via Navigator, large files (multiple Gigabytes) need to be copied onto the PACEdge device. CPL410, CPE400, and RXi2-LP have relatively weak processors and a lower amount of memory, resulting in heavy memory paging and high CPU load. When performing these operations expect that it will take some time to copy the files and for the CPU to settle down. Wait until copied files show up in the Navigator window, optionally observe CPU and memory utilization and give some time to settle down. It could take 15-20 min. |
| Low disc space on RXi2-LP | RXi2-LP 32GB SSD variant might have insufficient disc space to make a PACEdge upgrade to v2.2.2 via Navigator. The minimum space required on /home partition is 7GByte. Given that update is performed in two steps (OS and Applications), after the OS upgrade deletes files used for the upgrade. If disc space is still insufficient, then use an alternative upgrade method via a USB stick as documented in PACEdge User Manual. |
| The cockpit shows failing services | PACEdge is based on Ubuntu Server operating system, which comes with some services that do expect Internet connectivity. Since PACEdge is frequently installed in networks that do not have internet access Cockpit might report that some services, such as Network Manager Wait Online, have failed. This is normal and will not degrade PACEdge operation. |
| Time and Time Zone setting | PACEdge by default is configured to get local time and time zone via NTP protocol. If installed in a network that does not have an NTP server, please verify the time and time zone settings and adjust as necessary. Failure to do so might result that Grafana is not showing the data as expected. |
| Restoring PACEdge from the USB image requires reloading the Movicon project | When restoring PACEdge from backup on a USB stick the MQTT Client driver in Connexx may fail to connect to the MQTT broker. In such a case, reload the Movicon project using Movicon.NEXT Editor. |

| | |
|---|--|
| Changes in Connex MQTT Client | If converting a Movicon project created using Movicon.NEXT version v4.1 or older you might have to adjust MQTT Client settings. Make sure that in Channel Settings, the Client Identifier field is populated, and the maximum number of pending requests is set to more than 0, 5 is a good starting point. |
| Multiple instances of I/O Data Servers and WebHMI Servers are running | When deploying a new Movicon project or updating an existing one, users should stop and restart all running servers before continuing. Deploying or updating a project without restarting servers may lead to multiple instances of servers running. Users should expand the Advanced Servers Start menu to stop all running servers, then start the required servers one by one. |

Problems Resolved in Current Release

| Subject | Description |
|---|--|
| Portainer, Telegraf, and Movicon project Deploy passwords need to be changed manually | PACEdge v2.2.0 Password Management utility now automatically changes user role passwords in each of PACEdge Applications. Note that passwords in Cockpit/Linux still need to be changed via Cockpit. |

Operational Notes

PACEdge Upgrade to v2.2.0 Notes:

- Note that starting from PACEdge v2.2.0 upgrades will be split into two packages: Ubuntu Linux Operating System update and PACEdge Application update. This is done so that the user could choose to only update the OS portion but continue to use PACEdge Applications as is.
- Only PACEdge version v2.1 or v2.1.1 can be upgraded to PACEdge version 2.2.0. When upgrading from older PACEdge 2.0 or PACEdge 1.0 please first upgrade to PACEdge v2.1 and then proceed to upgrade to v2.2.0
- For detailed instructions and step-by-step procedures please consult PACEdge User Manual.

General Contact Information

Home link: <http://www.emerson.com/industrial-automation-controls>

Knowledge Base: <https://www.emerson.com/industrial-automation-controls/support>

Technical Support

Americas

Phone: 1-888-565-4155
1-434-214-8532 (If toll-free option is unavailable)

Customer Care (Quotes/Orders>Returns): customercare.mas@emerson.com
Technical Support: support.mas@emerson.com

Europe

Phone: +800-4444-8001
+420-225-379-328 (If toll-free option is unavailable)

Customer Care (Quotes/Orders>Returns): customercare.emea.mas@emerson.com
Technical Support: support.mas.emea@emerson.com

Asia

Phone: +86-400-842-8599
+65-6955-9413 (All other Countries)

Customer Care (Quotes/Orders>Returns): customercare.cn.mas@emerson.com
Technical Support: support.mas.apac@emerson.com

Any escalation request should be sent to mas.sfdcescalation@emerson.com

Note: If the product is purchased through an Authorized Channel Partner, please contact the seller directly for any support.

Emerson reserves the right to modify or improve the designs or specifications of the products mentioned in this manual at any time without notice. Emerson does not assume responsibility for the selection, use, or maintenance of any product. Responsibility for proper selection, use, and maintenance of any Emerson product remains solely with the purchaser.

© 2022 Emerson. All rights reserved. Emerson Terms and Conditions of Sale are available upon request. The Emerson logo is a trademark and service mark of Emerson Electric Co. All other marks are the property of their respective owners.

